

BULB HOLDER CONTROLLER(CANDELABRA)

JL-312C



PRODUCT SUMMARY

The JL-312C light controller product is a smart light controller developed based on the E26 adaptor. It uses a light sensor to detect ambient light level, to switch the bulb automatically. It is applicable to work with CFL/LED bulbs also.

FEATURES

- Standard E12 interface
- Self-sensing light switch
- Workable with CFL/LED

SPECIFICATIONS

Model No.	JL-312C	
Rated Voltage	120VAC	
Applicable Voltage Range	102~132VAC	
Rated Frequency	50/60Hz	
Rated Loading	60W Tungsten	0.5A e-Ballast
Power Consumption	0.2W Max.	
Turn On Level	16Lx (±15) Natural light	
Turn Off Level	64Lx (±15) Natural light	
Ambient Temperature	-40℃ ~ +70℃	
Related Humidity	96%	
Adapter	E12	
Failure Mode	Fail-Off	
Zero Crossing Control	Built-in	
Certifications	 	